

# Cordless Cyclone Cleaner DCL501















Filtration system with cyclone separation





Lightweight (with BL1815N) 3.1kg

#### Long lasting powerful suction

Cyclonic system separates large dust particles from fine dust particles so that only fine dust particles are captured on the filter to reduce clogging for longer powerful suction. HEPA filter\* is used for clean environments.

\*HEPA filter: 99.97% or more collection efficiency of airborne particle 0.3µm in diameter is defined by EN standard.

# Long run time and lightweight cleaner design

Achieved by using BL motor.



#### Easy dust disposal

- Dust cup can be removed for easy dust disposal simply by pulling up the cup release lever then by pushing the release button.
- The dust cup and the filter are washable in water.









#### Filter cleaning lever

After every use, simply move the lever side to side to remove dust from the filter.













- 1. Orange LED indicator for filter cleaning warning
- 2. Red LED indicator for battery capacity warning

#### **Continuous run time** On a single full battery charge: minute

Li-ion Battery		Continuous run time High / Low	Charger
with Battery fuel gauge	1.5Ah BL1815N*	8 / 19 min.	Fast charger DC18RC  DC18SD
BL1860B *without Battery fuel gauge	3.0Ah BL1830B	17 / 38 min.	
	4.0Ah BL1840B	23 / 51 min.	
	5.0Ah BL1850B	29 / 64 min.	
	6.0Ah BL1860B	35 / 77 min.	

## Cordless Cyclone Cleaner

#### **DCL501**

**Electronic 2-Speed** 

Soft Start

Revolving Hose

Capacity Continuous Use (min.)

Max Air Flow
Max Sealed Suction
(water column)
Dimensions
(L x W x H)

Net weight

250 mL with BL1860B (High): 35 with BL1860B (Low): 77 1.3 m³/min 6.6 kPa (660 mmH<sub>2</sub>O) 352x189x252mm (13-7/8"x7-7/16"x9-7/8") BL1815N: 3.1 kg (6.8 lbs.)

BL1860B: 3.3 kg (7.4 lbs.)

Standard Equipment:

 $Shoulder \ Belt, \ Crevice \ Nozzle, \ Cleaning \ Brush, \ Floor \ Nozzle, \ Zoom \ Pipe, \ Hose, \ Hose \ Hook$ 

weight according to EPTA-Procedure 01/ver.2.1 Items of standard equipment and specifications may vary by country or area.

### Makita Corporation

3-11-8 Sumiyoshi-cho, Anjo, Aichi, 446-8502 Japan